















2

D	1	V	W		
Directional control valve	Size DIN NG06 CETOP 03 NFPA D03	3-chamber valve	Wet pin armature solenoid, threaded in tube	Spool type	Spool position

3 position spools	
Code	Spool type a 0 b
001	
002	
003	
004	
005	
006	
007	
008 [1]	
009 [1]	
010	
011	
014	
015	
016	
021	
022	
031	
032	
034	
035	
061	
081	
082	
102	
204 [1]	
205 [1]	

2 position spools	
Code	Spool type a b
020	
026	
030	
083 [1]	
101	
208	

3 position spools			
Code	Spool position		
C			**3 positions.** **Spring offset in position “0“.** **Operated in position “a“ or “b“.**
	Standard	Spool type 008,009, 204, 205	
E	 **Operated in position “a“.**	 **Operated in position “b“.**	**2 positions.** **Spring offset in position “0“.**
F	 Spring offset in position “b“.	 Spring offset in position “a“.	2 positions. Operated in position “0“.
K	 **Operated in position “b“.**	 **Operated in position “a“.**	**2 positions.** **Spring offset in position “0“.**
M	 Spring offset in position “a“.	 Spring offset in position “b“.	2 positions. Operated in position “0“.

2 position spools			
Code	Spool position		
	Standard	Spool type 083	
B			**2 positions.** **Spring offset in position “b“.** **Operated in position “a“.**
D			**2 positions.** **Operated in position “a“ or “b“.** **No center or offset position.**
H			**2 positions.** **Spring offset in position “a“.** **Operated in position “b“.**

[1] Consider specific spool position.

[2] To be used in combination with rectifier plugs at 120 VAC / 230 VAC power supply.

[3] DC only

Tel: +45 63 12 83 00 | Email: ps@hymatik.com | www.hymatik.com | Hvidkaervej 27a, DK-5250 Odense SV, Denmark



Code	Solenoid option
omit	**manual override (standard)**
T	without manual override
S2 [3]	Soft shift orifice size 0.5 mm.
S3 [3]	Soft shift orifice size 0.75 mm.
4N [3]	with lockable manual override

Code	Voltage
K	**12 V =**
J	**24 V =**
U [2]	98 V =
G [2]	205 V =
Y	110 V 50 Hz / 120 V 60 Hz
T	230 V 50 Hz / 240 V 60 Hz

Code	Seals
N	**NBR**
V	FPM

Bold letters =
Short-term availability

Further spool types, solenoid voltages and connectors on request.

Tel: +45 63 12 83 00 | Email: ps@hymatik.com | www.hymatik.com | Hvidkaervej 27a, DK-5250 Odense SV, Denmark