TH8E-800-CM

Strong Crimping Press

- Crimps
  - all Parker *No-Skive* fittings ..... up to size -32
  - Industrial hose ..... up to 4" (DN 100)
  - SAE 100 R13 / SAE 100 R15 hose with Parker *No-Skive* fittings ..... up to size -32
  - SAE 100 R15 hose with ParLock fittings V4 and V6 ... up to size -20
- Adjustable crimper electronic system C and 3 different crimp programs, manual opening and closing, semi-automatic opening and closing, semi-automatic opening and closing with foot switch or depth stop
- It is possible to crimp small diameters with an adapter die set



Primary Applications

Hose assembly workshops with small series production and services at certified distributors, ParkerStores and hose workshops in the maintenance areas at OEM customers

Restrictions

Not for ParLock hose fittings in size -24 and size-32 (fittings series V4 and V6).
There could be interference with long drop elbow fittings.

Technical / Order Data

Crimping Press TH8E-800-CM with – adapter die set PB237.239.2L2 – quick change tool QDC239.5 – die set packet (12 mm – 74 mm) PBSET-TH8-800 Attention: Delivery without oil or connecting plug	Electrical power		230-480 V / 50-60 Hz / 3 PH / 4 kW
	Crimp force		220 t
	Control system		C-Touch
	Crimp range		139 mm
	Noise level		70 dB (A)
	Colour		black/silver
	Dimensions		L 690 x W 720 x H 1400 mm
	Oil tank capacity		70 l
	Weight	without oil	440 kg
		with oil	510 kg
	Part Number		**TH8E-800-CM**
TH8E-800	Electrical power		400 V / 50 Hz / 3 PH / 4 kW
	Control system		micrometer
	Part Number		**TH8E-800**
Adapter die set	**Part Number**		**PB237.239.2L2**
Depth stop	**Part Number**		**TA800/A**
Die rack	**Part Number**		**QDS239S**
Die set packet, Ø 12 – 74: PB239-65-12, PB239-65-14, PB239- 65-17, PB239-65-20,PB239-65-22, PB239-65-24, PB239-65-26, PB239-80-28, PB239-80-31, PB239-80-32, PB239-80-36,PB239-80-38,PB239-80-40, PB239-80-44, PB239-100-50, PB237L-54, PB237L-57, PB237L -62, PB237L -67, PB237L-71, PB237L-74	**Part Number**		**PBSET-TH8E-800**
Foot switch	**Part Number**		**FU-HMX**
Mirror set	**Part Number**		**SHS-800**
Quick change tool	**Part Number**		**QDC239.5**

Tel: +45 63 12 83 00 | Email: ps@hymatik.com | www.hymatik.com | Hvidkaervej 27a, DK-5250 Odense SV, Denmark